

SPECIFICATION SHEET

JFW MODEL 50RF-038

RF FUSEHOLDER

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Description	RF Fuseholder with BNC male/female
Frequency Range	DC-1000 MHz
Impedance	50 Ohms nominal
VSWR	1.5:1 maximum DC-500 MHz
	1.7:1 maximum 500-1000 MHz (with 1/16 Amp fuse)
	1.2:1 maximum DC-500 MHz
	1.4:1 maximum 500-1000 MHz (with 1/8 or 1/4 Amp fuse)
Insertion Loss	2.0 dB maximum (1/16 Amp fuse)
	0.5 dB maximum (1/8 Amp fuse)
	0.3 dB maximum (1/4 Amp fuse)
RF Fusing Level	+23 dBm (195 mW) (1/16 Amp fuse)
	+29 dBm (785 mW) (1/8 Amp fuse)
	+35 dBm (3.13 W) (1/4 Amp fuse)
Fuse Rating	At 100% of rated current: 4 hours minimum
	At 200% of rated current:
	1/16 A 1 sec max (0.015 sec typical) 1/8 A 1 sec max (0.04 sec typical) 1/4 A 1 sec max (0.1 sec typical)
RF Connector	BNC male/female
Physical Size	See outline drawing 092-5140

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	11/15/2006		CLK 11/15/2006				
26364	03/02/2016	A	BAC 03/02/2016				