

SPECIFICATION SHEET

JFW MODEL 50P-1857

SOLID STATE PROGRAMMABLE ATTENUATOR

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	200-6000 MHz
Impedance	50 Ohms nominal
Attenuation Range	0-95 dB in 1 dB steps
Attenuation Steps	1, 2, 4, 8, 16, 32 and 32 dB
VSWR	2.0:1 maximum
Attenuation Accuracy (guaranteed monotonic)	± 0.50 dB 1-7 dB ± 1.00 dB 8-11 dB ± 1.25 or 4% 12-95 dB (whichever is greater)
Insertion Loss	8 dB maximum 3.7 dB typical @ 200 MHz 4.0 dB typical @ 800 MHz 4.8 dB typical @ 2000 MHz 7.5 dB typical @ 6000 MHz
RF Input Power	+20 dBm (operating) +25 dBm (no damage)
Switching Speed	1 microsecond maximum 0.7 microseconds typical
DC Supply	+5Vdc @ 50mA nominal
Control Logic (7 Lines)	TTL Low for Thru Path TTL High for Attenuation
DC Connector	T&B #609-1007
RF Connector	SMA female
Operating Temperature Range	0°C to +70°C
Physical Size	See outline drawing 092-6246

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	08/05/2009		CLK 08/05/2009				
18188	01/26/2010	A	CLK 01/26/2010				