

SPECIFICATION SHEET**JFW MODEL 50SA-248****SWITCH ASSEMBLY**JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	DC-18 GHz
Configuration	Two 1P2T Failsafe Electromechanical RF Switches
Impedance	50 Ohms nominal
VSWR	1.10:1 maximum DC-1 GHz 1.15:1 maximum 1-4 GHz 1.20:1 maximum 4-8 GHz 1.30:1 maximum 8-12 GHz 1.35:1 maximum 12-18 GHz
Insertion Loss	0.10 dB maximum DC-1 GHz 0.15 dB maximum 1-4 GHz 0.20 dB maximum 4-8 GHz 0.30 dB maximum 8-12 GHz 0.35 dB maximum 12-18 GHz
Isolation	85 dB minimum DC-1 GHz 80 dB minimum 1-4 GHz 70 dB minimum 4-8 GHz 65 dB minimum 8-12 GHz 60 dB minimum 12-18 GHz
RF Input Power (cold switched)	400 Watts average DC-200 MHz 300 Watts average 200-500 MHz 200 Watts average 500-1000 MHz 100 Watts average 1-4 GHz 90 Watts average 4-8 GHz 70 Watts average 8-12 GHz 60 Watts average 12-18 GHz
Switching Speed	15 milliseconds (after command is received and processed) (3 milliseconds typical processing time)
Manual Control	Keypad and LCD display
Remote Control	Ethernet (10/100) and RS-232
Remote Commands	Set Switch (SSx y) Read Switch (RSx) Identification (IDN) Change Baud Rate (CBx)
AC Supply	100-240 VAC @ 47-63 Hz

--CONTINUED--

SPECIFICATION SHEET

JFW MODEL 50SA-248

SWITCH ASSEMBLY

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

RF Connector SMA female
Operating Temperature Range 0°C to +50°C
Physical Size See outline drawing 092-6399



ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	12/09/2009		TRS 12/09/2009				