

SPECIFICATION SHEET

JFW MODEL 57Z-3G AND 75Z-3G

IMPEDANCE MATCHING PAD

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range DC-3000 MHz

Impedance 57Z-3G: 75 Ohm female
50 Ohm male
75Z-3G: 50 Ohm female
75 Ohm male

VSWR 1.2:1 maximum DC-1500 MHz
1.35:1 maximum 1500-3000 MHz

Attenuation Loss ± 0.3 dB DC-1500 MHz
(above 5.7 dB nominal) ± 0.5 dB 1500-3000 MHz

RF Connector BNC, TNC, N, 2.4mm or SMA (50 Ohm side)
BNC, TNC, N or F (75 Ohm side)

Physical Size See outline drawing:
092-4560 57Z-3G (BNC M/BNC F)
092-4561 57Z-3G (BNC M/N F)
092-4567 57Z-3G (N M/BNC F)
092-4563 57Z-3G & 75Z-3G (N M/N F)
092-4558 57Z-3G (SMA M/F F)
092-4600 57Z-3G (SMA M/F M)
092-5972 57Z-3G (SMA M/BNC F)
092-6272 57Z-3G (SMA F/BNC F)
092-4551 57Z-3G (N M/F F)
092-7132 57Z-3G (N M/F M)
092-4559 75Z-3G (F M/SMA F)
092-4564 75Z-3G (N F/F M)
092-4562 75Z-3G (N M/BNC F)
092-6458 75Z-3G (N M/2.4mm)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
9999	03/03/2004	D	SL 03/03/2004	17613	08/27/2009	I	SMR 08/27/2009
15178	01/14/2008	G	TRS 01/14/2008	18238	02/11/2010	J	SMR 02/11/2010
16469	11/03/2008	H	SMR 11/03/2008	20830	11/01/2011	K	BAC 11/01/2011