

SPECIFICATION SHEET
JFW MODEL 50KFA-074 BNC
FIXED ATTENUATOR KIT

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Description	Kit of RF components supplied together in a case
Frequency Range	DC-2200 MHz
Impedance	50 Ohms nominal
RF Connectors	BNC
RF Input Power	1 Watt average
Parts Included	(1 piece) 3dB fixed attenuator, BNC male/female (1 piece) 6dB fixed attenuator, BNC male/female (1 piece) 10dB fixed attenuator, BNC male/female (1 piece) 20dB fixed attenuator, BNC male/female (1 piece) Termination BNC male
Model Numbers for Each Individual Part	50F-003 BNC (3dB Fixed Attenuator) 50F-006 BNC (6dB Fixed Attenuator) 50F-010 BNC (10dB Fixed Attenuator) 50F-020 BNC (20dB Fixed Attenuator) 50T-319 BNC M (Termination)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	09/24/2014		TRS 09/24/2014				