

SPECIFICATION SHEET
JFW MODEL 50P-1209
RELAY PROGRAMMABLE ATTENUATOR

JFW Industries, Inc.
 Phone: 317-887-1340
 sales@jfwindustries.com
 www.jfwindustries.com

| | |
|-----------------------------|--|
| Frequency Range | DC-2500 MHz |
| Impedance | 50 Ohms nominal |
| Attenuation Range | 0-15.5 dB in 0.5 dB steps |
| Attenuation Steps | 0.5, 1, 2, 4, and 8 dB |
| VSWR | 1.6:1 maximum |
| Attenuation Accuracy | 0.5 dB Pad ± 0.2 dB DC-2500 MHz 1, 2, 4, 8 dB Pads ± 0.2 dB or 2% DC-1000 MHz ± 0.3 dB or 3% 1000-2500 MHz |
| Insertion Loss | 0.8 dB maximum at 500 MHz 1.5 dB maximum at 1000 MHz 3.0 dB maximum at 2500 MHz |
| RF Input Power | 0.5 Watts average 100 Watts peak |
| Switching Speed | 6 milliseconds maximum |
| Control | +12 Vdc at 15 mA per relay |
| RF Connector | BNC, SMA, TNC or N female |
| Operating Temperature Range | -20°C to +85°C |
| Physical Size | See outline drawing 092-2611 |

| ECR/ECN # | DATE | REV | APPR / DATE | ECR/ECN # | DATE | REV | APPR / DATE |
|-----------|------------|-----|----------------|-----------|------------|-----|----------------|
| 1001 | 03/19/1998 | A | | 12783 | 05/10/2006 | D | TRS 05/10/2006 |
| 4434 | 01/21/2004 | C | CLV 01/22/2004 | 14364 | 07/06/2007 | E | TRS 07/06/2007 |
| 9999 | 09/26/2002 | B | TRS 10/01/2002 | 14398 | 07/11/2007 | F | TRS 07/12/2007 |