

SPECIFICATION SHEET**JFW MODEL 50P-2101****SOLID STATE PROGRAMMABLE ATTENUATOR**

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	0.1-18 GHz
Impedance	50 Ohms nominal
Attenuation Range	0-63 dB in 0.5 dB steps
Attenuation Steps	0.5, 1, 2, 4, 8, 16 and 31.5 dB
VSWR	1.6:1 maximum 0.1-6 GHz 2.0:1 maximum 6-18 GHz
Attenuation Accuracy	± 0.25 dB 0.5-3.5 dB ± 0.50 dB 4-14.5 dB ± 1.00 dB or 3% 15-63 dB (whichever is greater)
Insertion Loss	7.0 dB maximum 2.0 dB typical @ 0.1 GHz 2.7 dB typical @ 3 GHz 3.2 dB typical @ 6 GHz 4.5 dB typical @ 12.4 GHz 6.4 dB typical @ 18 GHz
RF Input Power	+24 dBm (operating - Input Side) +15 dBm (operating - Output Side) +25 dBm (no damage - Input Side) +16 dBm (no damage - Output Side)
Switching Speed	1 microsecond maximum 0.35 microseconds typical
DC Supply	+5 Vdc @ 2mA nominal
Control Logic (7 Lines)	TTL Low for Thru Path (+0 to +0.8 Vdc) TTL High for Attenuation (+2 to +5 Vdc)
DC Connector	3M #D2510-6002 (Mating Connector 3M #3473-6610)
RF Connector	SMA
Operating Temperature Range	-40°C to +85°C
Outline Drawing Numbers	092-9403-11 (SMA female/female) 092-9403-12 (SMA male/female)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	09/12/2019		CLK 09/12/2019	33270	03/28/2024	C	CLK 03/28/2024
30373	05/06/2020	A	TRS 05/06/2020				
30836	12/21/2020	B	TRS 12/21/2020				