

**SPECIFICATION SHEET****JFW MODEL 50KFA-074 N****FIXED ATTENUATOR KIT**

JFW Industries, Inc.  
Phone: 317-887-1340  
sales@jfwindustries.com  
www.jfwindustries.com

Description	Kit of RF components supplied together in a case
Frequency Range	DC-2200 MHz
Impedance	50 Ohms nominal
RF Connectors	N
RF Input Power	1 Watt average
Parts Included	(1 piece) 3dB fixed attenuator, N male/female (1 piece) 6dB fixed attenuator, N male/female (1 piece) 10dB fixed attenuator, N male/female (1 piece) 20dB fixed attenuator, N male/female (1 piece) Termination N male
Model Numbers for Each Individual Part	50F-003 N (3dB Fixed Attenuator) 50F-006 N (6dB Fixed Attenuator) 50F-010 N (10dB Fixed Attenuator) 50F-020 N (20dB Fixed Attenuator) 50T-335 N M (Termination)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	09/24/2014		TRS 09/24/2014				