

SPECIFICATION SHEET

JFW MODEL 50PD-134

3 WAY RESISTIVE POWER DIVIDER

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

| | |
|-----------------------------|---|
| Frequency Range | DC-2000 MHz |
| Impedance | 50 Ohms nominal |
| VSWR | 1.4:1 maximum 1.2:1 typical |
| Insertion Loss | 9.5 dB ± 0.5 dB |
| Amplitude Tracking | ± 0.5 dB |
| RF Input Power | 2 Watts average @ 25°C 100 Watts peak (1 microsecond) |
| Operating Temperature Range | -40°C to +85°C |
| RF Connector | N, TNC, or BNC (male or female) |
| Physical Size | See outline drawings: 092-2328-03 (50PD-134 N) 092-6646-03 (50PD-134 BNC) 092-7002-03 (50PD-134 TNC) |

| ECR/ECN # | DATE | REV | APPR / DATE | ECR/ECN # | DATE | REV | APPR / DATE |
|-----------|------------|-----|----------------|-----------|------------|-----|----------------|
| 961 | 02/05/1998 | B | | 19960 | 04/07/2011 | E | TRS 04/07/2011 |
| 9999 | 11/17/2002 | C | SL 11/27/2002 | 20281 | 06/29/2011 | F | TRS 06/29/2011 |
| 18885 | 07/15/2010 | D | TRS 07/15/2010 | 31756 | 04/29/2022 | G | TRS 04/29/2022 |