

SPECIFICATION SHEET**JFW MODEL 50PD-432****2 WAY RESISTIVE POWER DIVIDER/COMBINER**

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	DC-6000 MHz
Impedance	50 Ohms nominal
VSWR	1.5:1 maximum
Insertion Loss	6 dB $\pm$ 1.0 dB
Amplitude Tracking	$\pm$ 0.7 dB
RF Input Power	1 Watt average @ 25°C 100 Watts peak (1 microsecond)
RF Connector	N female
Physical Size	See outline drawing 092-2328-02



ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
3005	05/23/2002	C		18885	07/15/2010	F	TRS 07/15/2010
9999	12/20/2002	D	SL 01/14/2003	30297	03/24/2020	G	TRS 03/24/2020
16595	12/09/2008	E	TRS 12/09/2008	31757	04/29/2022	H	TRS 04/29/2022